

NHIC-4LMRAT

4" IC Air-Tight LED Dedicated New Construction Housing
(Compatible with Iolite / Cobalt / Marquise / Onyx / Pearl)

Type

Project

Catalog No.

Notes

PRODUCT DESCRIPTION

Dedicated new construction housing for use in insulated ceilings can be in direct contact with insulation.* Air-tight construction provides energy savings by reducing the flow of air through the ceiling. The housing is dedicated and labeled for use with LED retrofit luminaires.

FEATURES

- IC Air-Tight energy saving by reducing the flow of air through the ceiling
- Rated for direct contact with insulation
- cULus listed for damp location and through branch circuit wiring

CONSTRUCTION

Plaster Frame: High quality 0.04" steel die cut one piece frame.

Housing: 0.040 galvanized steel housing with riveted cap adjusts for ceiling thicknesses from 1/2" to 2". Spring brackets accept torsion wing trim springs; slots on socket plate surface accept standard coil springs.

Air Flow Restriction: Housing has factory installed gaskets to restrict airflow from room into ceiling plenum to <2CFM (cubic feet per minute) in accordance to ASTM 283.

Clearance: "IC" Insulated ceiling housings are direct contact rated. **Not to be used in direct contact with spray foam insulation.**

Bar Hangers: Two 13-3/4" to 24-1/2" adjustable bar hangers with captive nails are included on frame. Bar hangers are parallel to junction box, but can be repositioned 90° perpendicular to junction box if desired. "L" Shaped bar hanger foot to align to bottom of construction joist. A T-Bar notch allow for easy installation in a suspended ceiling.

Junction Box: Prewired 25 cubic inch 0.064" thick galvanized steel box with seven 1/2" trade size knockouts and snap on covers. All leads are #18AWG wire, the ground wire is connected to the bottom, and quick connectors are supplied on all leads. Maximum of 8 no. 12 AWG through branch circuit conductors suitable for at least 90°C permitted in junction box.

Romex Strain Relief: Junction box includes two Romex tabs with two slots at each tab for NM-cables of 12/2 to 14/2. The strain relief allows for easy installation and less materials.

ELECTRICAL

Input Voltage: 120/277V or 277V (must specify)
Socket: Quick connect for LED downlights
Operating Temperature: 122°F (50°C) max.
Dimming: Specified by downlight

Step Down Transformer (converts 277V input to 120V):

Optional 50W step down transformer installed (NHIC-4LMRAT/277). Maximum of 6 no. 12 AWG through branch circuit conductors suitable for at least 90°C permitted in junction box when used with step down transformer.

COMPATIBILITY

NIR-4: 4" Iolite Retrofit Downlights
NLCBC-469: 4" Cobalt Adjustable Downlight
NLCBC2-4: 4" Cobalt Click Downlights
NOX-4 / NOXAC-4 / NOXTW-4: 4" Onyx Downlights
NPR-4: 4" Pearl Series
NRMCS-4: 4" Marquise III Downlights

Emergency: Housing can be specified with an emergency battery installed on frame (Cobalt only). Requires top access.



- Up to 7.5W emergency illumination with LEDs
- Illumination Time: 90min
- Voltage: 120/277 VAC, 60Hz
- Output Voltage: 15.0-50.0 VDC
- Remote test switch included

LABELS AND LISTINGS

- cULus Listed for Damp Location (wet location when used with compatible downlight)
- Airtight in accordance to ASTM 283
- Certified to the high efficacy requirements of California Title 24 JA8-2022 (when used with compatible downlight)
- RoHS compliant



PRODUCT IMAGES & DIMENSIONS



4" IC Air-Tight LED Dedicated New Construction Housing

Catalog No.

NHIC-4LMRAT = 4" IC Air-Tight Housing, 120/277V input (120V Triac/ELV dimming)

NHIC-4LMRAT/277 = 4" IC Air-Tight Housing, 277V input with 50W Step Down Transformer

NHIC-4LMRAT/EM = 4" IC Air-Tight Housing with Emergency Battery and Remote Test Switch, 120/277V input (Cobalt only - EM required)

NHIC-4LMRAT/277EM = 4" IC Air-Tight Housing with Emergency Battery and Remote Test Switch, 277V input with 50W Step Down Transformer (Cobalt only - EM required)

NHIC-4LMRAT/4W = 4" IC Air-Tight Housing, 120/277V input (120V Triac/ELV/0-10V & 277V 0-10V dimming, Cobalt only - LE4 required)

NHIC-4LMRAT/6WEM = 4" IC Air-Tight Housing with Emergency Battery and Remote Test Switch, 120/277V input (120V Triac/ELV/0-10V & 277V 0-10V dimming, Cobalt only - LE4EM required)

Example: **NHIC-4LMRAT** = 4" IC Air-Tight LED Dedicated New Construction Housing, 120/277V input